

Changing a C75/A60/A45 PCB

IMPORTANT:- You must unplug the unit from the main supply before starting this procedure.

Health & Safety

CAUTION: This procedure is to be carried out by a competent person only.

Tools required. A pair of long nosed pliers and a flat blade screwdriver.



1. Unscrew retaining screw in Operator cover and remove.



2. Pull back black retaining clip and remove limit switch cable.



3. Remove receiver PCB.



4. Remove decoder PCB.

Check the wiring diagram is in the lid of the Operator before the next stage. If it is not, then carefully note the position and colour of wires and their connections before removing them.



7. Place new PCB on to the spacers. Press down firmly to engage barbs.



8. Replace wires back into position in both terminal blocks. (With long nosed pliers and screwdriver.)

9. Replace Decoder and Receiver PCB's.

10. Replace Limit switch cable.

11. Restore power to Unit.

12. You will now need to perform pressure learning procedures as described in the Installation Manual.